Packing station warning codes

Code	Cause	Action
E01	Open cover	Close the cover and press Start.
E02	Missing label roll	Fit a label roll in the holder.
E03	Paper jam	Switch off the printer and remove the jammed paper.
E04	Full output tray	Empty the output tray before restarting.
E05	Obstructed sensor	Remove the obstruction from the sensor window.
E06	Label not aligned	Adjust the guides to the edge of the label.

Before clearing a jam, isolate the packing station from its power supply. If a warning returns after the action, stop the unit and inform maintenance.

Packing station service codes

Code	Cause	Action
E07	Motor overheated	Switch off the unit and allow it to cool.
E08	Communication lost	Check the data cable at both ends.
E09	Low air pressure	Check the supply gauge and inform maintenance.
E10	Calibration failed	Run the calibration routine with an empty tray.
E11	Stop button engaged	Check the area before releasing the stop button.
E12	Overloaded scale	Remove the load and reset the scale to zero.

Do not open the electrical enclosure. Record the code and the action taken in the equipment log.